

Delock 2 > 1 Displayport KVM Switch USB and Audio for PC and Mac

Description

This Delock Displayport KVM switch is a convenient solution for connecting one monitor, TV etc. to two computers. Furthermore the USB ports enable you to connect a mouse, keyboard, hard disk and USB memory. By using the button or the remote control you can switch between both computers. In addition you can transmit audio signals in order to use a speaker and microphone with both computers.



Specification

- Connector:
 - 2 x Displayport female (connection for PC1 and PC2)
 - 1 x Displayport female (Monitor or TV)
 - 1 x HDMI-A female (Monitor or TV)
 - 3 x USB A female (mouse, keyboard, hard disk, USB memory etc.)
 - 2 x USB B female (connection for PC1 and PC2)
 - 2 x 3.5 mm stereo jack female (1 x for speaker, 1 x for microphone)
 - 1 x Sub-D 9 pin female RS232 (for configuration)
 - 1 x DC power connector
 - 1 x 3.5 mm stereo jack female for additional IR-receiver (optionally)
- 2 x switch button with LED indicator for source and sink
- Switching via button or remote control
- Resolution up to Full-HD 1080p
- Configuration and controlling the device via RS232 interface
- Colour: black
- Dimension (LxWxH): ca. 257 x 112 x 33 mm
- OS independent, no driver installation necessary

Item No. 11367



EAN	4043619113675
-----	---------------

Country of origin	China
-------------------	-------

System requirements

- 2 PCs / Mac with each 1 x Mini Displayport female + 1 x USB A female
- Additional 1 x 3.5 mm stereo jack for speaker, 1 x 3.5 mm stereo jack for microphone
- Monitor or TV with Displayport or HDMI interface

Package content

- Displayport KVM Switch USB and Audio
- 2 x cable USB A male to USB B male, length ca. 2 m
- 1 x cable DP male to Mini DP female, length ca. 0.9 m
- 2 x cable DP male to Mini DP male, length ca. 0.9 m
- External power supply 5 V / 2 A
- Remote control
- User manual

Package

- White Box

Images

