VS481A



4-Port HDMI Switch

The VS481A 4 Port HDMI Switch allows you to quickly and easily share your HDMI display device with 4 HDMI input sources.

The VS481A allows convenient switching between digital devices such as DVD players, Satelite receivers, Digital Camcorder. The VS481A allows you to select the desired input source via a remote control unit and pushbuttons located on the switch.














Features

- Allows up to four HDMI A/V source to be connected to one HDMI display
- Toggle between A/V sources using remote control or front panel pushbuttons
- Supports high-resolution video HDTV resolutions of 480p, 720p, 1080i, 1080p (1920x1080); VGA, SVGA, SXGA, UXGA (1600x1200) and WUXGA(1920x1200)
- Supports 12-bit Deep Color for HDMI formats
- Supports Dolby True HD and DTS HD Master Audio
- Up to 60 Hz refresh rate
- Long distance transmission up to 20 m (24 AWG) and 15 m (28 AWG)
- Built-in bi-directional RS-232 serial remote port for high-end system control
- Plug-and-play no software installation required
- DDC Compatible
- HDMI 1.3b compliant
- HDCP 1.1 compliant
- Supports HDMI Type A 19-pin female connector
- Signaling rates up to 2.25 Gbits in support of 1080p display
- All-metal casing
- LED indication of video source devices
- Easy and affordable way to add four HDMI inputs to your home theater system

Setup



Specifications -----

Function			VS481A
Display Connections			1
Connectors	Device	HDMI In	4 x HDMI Type A Female (Black)
	Display	HDMI Out	1 x HDMI Type A Female (Black)
	RS-232 Port		1 x DB-9 Female (Black)
	Power		1 x DC Jack
LEDs	On Line		4 (Orange)
	Selected		4 (Green)
Video			HDTV resolutions of 480p, 720p, 1080i, 1080p (1920x1080); VGA, SVGA, SXGA, UXGA (1600x1200) , WUXGA(1920x1200)
Power Consumption			DC5.3V, 2.4W
Environment	Operating Temp.		0-50°C
	Storage Temp.		-20-60°C
	Humidity		0-80% RH, Non-condensing
Physical Properties	Housing		Metal
	Weight		0.47 kg
	Dimensions (L x W x H)		20.00 X 8.00 X 2.50 cm

^{*} The specifications and pictures are subject to change without notice.

