



## AW1 WIFI ALARM SYSTEM



### Security Simplified

The AW1 is ready to go as soon as you connect it to your WiFi router. Add wireless sensors and accessories to the system directly on your smartphone app anytime as you wish.



## AW1 WIFI ALARM SYSTEM



### Real-time Notification

When AW1 is triggered, it goes off loud, formidably so. The system will also send you push notifications in real time, so you are always in the know no matter where you are.



### Event History

AW1 allows you to view 100 latest system activities and alarm events.



### On Guard 24/7

AW1 works around the clock and stays vigilant at all times without dozing off (like security guards do). Its backup battery ensures 20 hours of extra vigilance in the event of power outage or sabotage.



### On A Schedule

You can preset an Arm and Disarm schedule for your weekday routine.

### System Specifications

EAN Code: **8718868403711**

Power Supply **DC12V 500mA**

Battery **3.7V 600mAh Li-ion x 1pc**

Battery Recharge Cycle **300 times**

WiFi **IEEE 802.11b/g/n, 2.4GHz**

Standby Current **<27mA**

Alarm Current **<180mA**

Internal Siren **85dB**

Expandable Accessories **10 remote controls, 30 sensors**

Radio Frequency **315MHz or 433MHz**

Housing Material **ABS plastic + Acrylic**

Operating Condition **Temperature: 0°C~+55°C**

**Relative Humidity: <80% (non-condensing)**

Dimensions (L x W x H) **87.5 x 81.5 x 12mm**

Box Size: **208 x 138 x 98mm (L x W x H)**

### Package Details

AW1 Control Panel **x 1**

PIR-910 Pet-immune PIR Motion Detector **x 1**

DWC-102 Door/ Window Contact **x 1**

RC-80 Remote Control **x 2**



[www.chuango.com](http://www.chuango.com)