



Item No. 62795 Delock Adapter USB Type-C[™] male > HDMI female (DP Alt Mode) 4K 30 Hz

Description

This Delock adapter is suitable for the connection of an HDMI monitor to a computer with USB-C™ interface and Displayport alternate mode support. Thus, the adapter can be connected to different laptops like Macbook, Chromebook and similar. In addition, the adapter can also operate on a Thunderbolt™ 3 interface.



Note

When using the Macbook, first connect the adapter and then the HDMI cable.

Specification

- Connector:
- 1 x USB Type-C[™] male >
- 1 x HDMI-A 19 pin female
- Chipset: Cypress + Chrontel CH7525
- Displayport 1.2a and High Speed HDMI with Ethernet (HEC) specification
- Signal direction: USB Type-C[™] input > HDMI output
- Resolution up to 1920 x 1200 @ 60 Hz / 3840 x 2160 @ 30 Hz (depending on the system
- and the connected hardware)
- Transfer of audio and video signals
- Supports 3D displays
- Supports HDCP 1.4
- USB bus powered
- Plug & Play
- Plastic housing with inner metal shell
- Cable length without connector: ca. 8 cm
- Colour: black

System requirements

- Windows 7/7-64/8.1/8.1-64/10/10-64, Windows 10 Mobile, Mac OS 10.11.4
- PC or laptop with a free USB Type-C[™] port and Displayport alternate mode or
- PC or laptop with a free Thunderbolt[™] 3 port

Package content

USB-C[™] to HDMI Adapter

ltem No. 62795

EAN: 4043619627950

Country of origin: China

Package: Retail Box







Images







General	
function:	Plug & Play
Specification:	Displayport 1.2
	High Speed HDMI with Ethernet
	HDCP 1.4
Supported operating system:	Mac 10.11.4
	Windows 7 32-bit
	Windows 7 64-bit
	Windows 8.1 32-bit
	Windows 8.1 64-bit
	Windows 10 32-bit
	Windows 10 64-bit
	Windows 10 Mobile
Interface	
Output:	1 x HDMI-A 19 pin female
Input:	1 x USB Type-C™ male
Technical characteristics	
Chipset:	Cypress
	Chrontel CH7525
Maximum screen resolution:	3840 x 2160 @ 30 Hz
	1920 x 1200 @ 60 Hz
Signal transmission:	video
	audio
Physical characteristics	
Cable length:	8 cm
Connector finishing:	nickel-plated
Colour:	black