

Product Highlights

Transform Your Mobile Device into a Pet Monitor

Whether you're at home or away at work, you can conveniently watch over your pet on your smartphone, tablet or computer

Full-Featured yet Simple to Use

The free mobile app gives you effortless access to advanced features like 2-way audio², notifications, snapshots and more

Perfect at Home or Away

Mount the camera at home or take it with you when going on a family trip; it's easy to keep an eye on your pet no matter where you go



DCS-800L/P

EyeOn™ Pet Monitor

Features

Camera

- Night vision with infrared LEDs that turn on automatically when it gets dark
- 802.11n wireless lets you place the camera anywhere
- Can be powered by an external USB battery¹
- Interchangeable yellow, blue and pink accent colour rings

Intelligent Pet Monitoring

- Sound detection alerts you to loud noises, such as your dog barking or cat meowing
- Motion detection lets you know if the camera detects movement
- Notifications can be sent to your mobile device when motion or sound is detected
- Two-way audio lets you hear and talk back to your pet²

Monitor from your Mobile Device or Computer

- Uses the free mydlink™ Lite app for iOS and Android devices
- The mydlink™ Lite app helps you set up your device and gives you easy access to all functions
- Monitor from your computer through the secure mydlink™ web portal

Keep an eye on your beloved pet with the DCS-800L/P EyeOn™ Pet Monitor. This portable camera transforms your mobile device into a versatile, yet easy to use pet monitor. Connect to the camera wirelessly or over the Internet so you can check on your pet no matter where you are. It includes a wide array of features to help you look after your pet including night vision, motion and sound detection.



Peace of Mind, Anywhere, Anytime

The EyeOn™ Pet Monitor is specially designed to make it easy for you to care for your pet. It can detect movement and loud noises such as barking or meowing, and alert you via push notification. Its versatile all-day monitoring turns on night vision automatically when it gets dark, giving you a clear picture day or night so you can keep an eye on things anytime. It's perfect for use in the home, or even when you're away; it's mydlink™-enabled, which means that you can check on your pet remotely and securely over the Internet.



Perfectly Portable for Instant Monitoring Anywhere

You can take the EyeOn™ Pet Monitor with you when travelling with your pet, even when there is no available Internet connection. Just connect your mobile device to the EyeOn™ Pet Monitor's wireless network for instant local monitoring, making it perfect for family holidays or just visiting friends. You can even connect it to an external USB battery¹ for total portability!

mydlink Super Simple to Use




Getting started is quick and easy; the free mydlink™ Lite app for iOS and Android mobile devices not only guides you step by step through the setup process but also gives you an easy to use interface for all the advanced features of the EyeOn™ Pet Monitor. Check on your pet at a glance, pinch to zoom in and out with ease or play one of five gentle lullabies to soothe and calm your pet. You can even take snapshots and save them directly to your mobile device!

Just download the free mydlink™ Lite app for your smartphone or tablet and you can quickly and easily setup and view your EyeOn™ Pet Monitor from anywhere with a wireless or 4G LTE/3G connection. You can also log onto the secure mydlink™ web portal on your computer to see what your pet is up to.

D mydlink™ Lite App


Download the free mydlink™ Lite app and start monitoring.

Setup in 3 simple steps!

Step 1 Install 	Step 2 Place 	Step 3 Monitor 
---	--	--



2-Way Audio²



Day & Night Vision



See up to 5m in the dark



Digital zoom up to 4x from your mobile device



Check in on your pet using your smartphone or tablet

Front View

Back View



Switchable Accent Rings



Remote viewing



Sound/motion detection



2-way audio²



Instant push alerts



Secure Connection



Take snapshots directly to your mobile device



4x digital zoom



Plays Lullabies

Technical Specifications

Camera

Camera Hardware Profile	<ul style="list-style-type: none"> • 1/5" VGA CMOS sensor • 5 metre IR light illumination distance • Minimum illumination: 0 lux with IR LEDs on • Built-in microphone and speaker • Digital zoom • Adjustable angle and pivot 	<ul style="list-style-type: none"> • Focal length: 2.44mm • Aperture: F2.4 • Angle of view: <ul style="list-style-type: none"> • (H) 57° • (V) 42° • (D) 68°
External Device Interfaces	<ul style="list-style-type: none"> • 802.11n wireless • Reset button 	<ul style="list-style-type: none"> • Direct button • Power port (microUSB)
LED	<ul style="list-style-type: none"> • Link/Activity/Power 	<ul style="list-style-type: none"> • Cloud/Direct Mode
Image Features	<ul style="list-style-type: none"> • Configurable image size 	<ul style="list-style-type: none"> • Time stamp overlay
Video Compression	<ul style="list-style-type: none"> • MJPEG format video compression 	<ul style="list-style-type: none"> • JPEG for still images
Video Resolutions	<ul style="list-style-type: none"> • 640 x 480 	<ul style="list-style-type: none"> • 320 x 240
Audio Support	<ul style="list-style-type: none"> • PCM 	
Pet Monitoring Features	<ul style="list-style-type: none"> • Sound detection with adjustable sensitivity • Motion detection with adjustable sensitivity 	<ul style="list-style-type: none"> • 2-way audio lets you listen and respond to your pet² • Sends notifications when sound or motion is detected
Mobile App	<ul style="list-style-type: none"> • mydlink™ Lite app available on the App Store and Google Play 	<ul style="list-style-type: none"> • Compatible with iPhone and iPad using iOS 5.1.1 or higher • Compatible with Android smartphones and tablets using Android 4.1 or higher

Network

Network Protocols	<ul style="list-style-type: none"> • IPv4 • ARP • TCP/IP • UDP • ICMP 	<ul style="list-style-type: none"> • DHCP client • HTTP • HTTPS (for configuration) • UPnP port forwarding
Security	<ul style="list-style-type: none"> • Administrator protection • Password authentication 	<ul style="list-style-type: none"> • HTTP authentication

Physical

Dimensions (L x W x H)	<ul style="list-style-type: none"> • 70 x 75 x 100 mm (2.8 x 3.0 x 3.9 inches) 	
Weight	<ul style="list-style-type: none"> • 108.2g (3.8 oz) 	
Power Input	<ul style="list-style-type: none"> • 5 V DC / 1.5 A, 50/60 Hz through power adapter 	<ul style="list-style-type: none"> • Can be powered by an external USB battery with at least 2 A output¹
Power Consumption	<ul style="list-style-type: none"> • 4.4 watts max. 	
Temperature	<ul style="list-style-type: none"> • Operating: 0 to 40 °C (32 to 104 °F) 	<ul style="list-style-type: none"> • Storage: -20 to 70 °C (-4 to 158 °F)
Humidity	<ul style="list-style-type: none"> • Operating: 20% to 80% non-condensing 	<ul style="list-style-type: none"> • Storage: 5% to 95% non-condensing
Certifications	<ul style="list-style-type: none"> • CE • CE LVD • FCC 	<ul style="list-style-type: none"> • IC • C-Tick

¹ USB battery not included, requires at least 2 A output. ² 2-way audio is half-duplex.



For more information: www.dlink.com

D-Link European Headquarters. D-Link (Europe) Ltd., D-Link House, Abbey Road, Park Royal, London, NW10 7BX. Specifications are subject to change without notice. D-Link is a registered trademark of D-Link Corporation and its overseas subsidiaries. All other trademarks belong to their respective owners. ©2013 D-Link Corporation. All rights reserved. E&OE.

Updated June 2014

D-Link®
Building Networks for People